S5110/ART 4B LITE one line video kit

Reference: S5110/ART 4B
Product code: 12205114B
EAN code: 8429898016528



Main characteristics

Soul video door panel kit with 2-wire technology.

- SOUL/1B vandal-proof outdoor panel for a call button.
- Monitor ART 4B LITE/G2+ 4.3" hands free.
- Power supply FA-G2+.

More information

ART 4B LITE/G2+ MONITOR
Hands-free monitor for surface installation.
4.3" screen with capacitive navigation buttons.
High efficiency loudspeakers.
Audio communications, video and secret door opening.
Video-spy functions, auto-start, doctor mode and do not disturb.
Intercommunication with other units of the house selectively.
Personalization of ring tones.
Connection to the entrance door pushbutton, which saves the use of the doorbell.
Output to auxiliary call repeater.
Dimensions: 110(W) x 155(H) x 14(D) mm.
Up to 4 monitors in the same house without additional power.
Power supply FA-G2+.
Use 12V d.c. lock release (does not include lock release).
Recommended lock release: CV-24P/UNI (20600252).

ANTI-VANDAL SOUL/1B PANEL
Zamak front in black finish.
CMOS 120º camera.
Vandal resistant (IK-07) and weatherproof (IP-44) door panel.
Auto-start LEDs depending on outdoor lighting.
Color guide icons indicate the different states of the system (call in progress, communication, door opening or occupied system).
Metallic call button.
Secret communication of audio, video and door opening.
Relay output for activation of two doors.
Connection to analog CCTV camera.
RFID proximity reader for 60 users (keys not included).
Surface installation.
Dimensions: 90(W) x 170(H) x 27(D) mm.

Accessories

- TAGSET/PROG user tag set
- TAGSET/5 user tag set
- CARDSET/5 user card set

Visit in the website: https://www.golmar.es/products/s5110-art-4b

Golmar Sistemas de Comunicación S.A.
Silici 13 • 08940 Cornellà de Llobregat (Barcelona) • Tel: +34 934 800 696 • Fax: +34 934 742 404 • golmar@golmar.es • www.golmar.es

S5110/ART 4B LITE one line video kit

Visit in the website: https://www.golmar.es/products/s5110-art-4b

Golmar Sistemas de Comunicación S.A.
Silici 13 • 08940 Cornellà de Llobregat (Barcelona) • Tel: +34 934 800 696 • Fax: +34 934 742 404 • golmar@golmar.es • www.golmar.es