GM-IPOP 40 proximity and Bluetooth wall-mounted reader

Reference: GM-IPOP 40
Product code: 20720004
EAN code: 8429898021140



Main characteristics

- Water-proof and vandal-proof 13.56MHz proximity reader and 2SAFE technology.
- Integrates BLE technology that allows the user to access via smartphone (requires the purchase of "PUNTOS BLE" (BLE POINTS)). The application for its use is K-APP available on Android and IOS.
- For IP OPENER and EASYGATE controllers.
- Suitable with CARDDOOR MF +,TAGDOOR MF+, GM-WEIPOP, ISOPROX and KEYPROX cards and keyfobs.
- IP65 and IK10 protection ratings
- Outdoor wall installation

Promotional video "Access via Bluetooth".
Promotional video "Bluetooth Management".
Dimensions: 47(W) x 90(H) x 23(D) mm

More information

Specifications	
Technology	2SAFE
Type Function	Slave
Reading / Detection Type	Proximity,Bluetooth
RFID Frequency (MHz)	13.56
RFID Reading /coverage distance (cm)	4
Use	Outdoor,Indoor
Mounting	Surface
Incorporates base	Yes
State LEDs	Yes
Input voltage	12Vdc
Powered by controller	Yes
Degree of protection (IK)	10
Degree of protection (IP)	65
Maximum working temperature (ºC)	60
Minimum working temperature (ºC)	-20
Dimensions - High (mm)	90
Dimensions - Width (mm)	47
Dimensions - Deep (mm)	23
Weight (gr.)	65

Accessories

- 1 door access control panel GM-IPOP-1P
- 4 door access control panel GM-IPOP-4P
- CARDDOOR MF+ Mifare Plus Proximity Card
- ISOPROX proximity card
- GM-WEIPOP RF/Proximity Mifare transmitter control for IPOP controllers
- 2 door access control panel GM-IPOP-2P
- GM-USBIPOP USB programmer for EasyGate and IP Opener controllers
- TAGDOOR MF+ Mifare Plus proximity keyfob
- KEYPROX proximity fob
- Points for using the BLE function in iP Opener

Visit in the website: https://www.golmar.es/products/gm-ipop-40

Golmar Sistemas de Comunicación S.A.
Silici 13 • 08940 Cornellà de Llobregat (Barcelona) • Tel: +34 934 800 696 • Fax: +34 934 742 404 • golmar@golmar.es • www.golmar.es

Visit in the website: https://www.golmar.es/products/gm-ipop-40

Golmar Sistemas de Comunicación S.A.
Silici 13 • 08940 Cornellà de Llobregat (Barcelona) • Tel: +34 934 800 696 • Fax: +34 934 742 404 • golmar@golmar.es • www.golmar.es